



ANDREA
COMMUNICATIONS

NC-185 VM

ON-EAR STEREO
PC HEADSET




- Exclusive noise-canceling microphone meets the highest standards to receive the coveted “6 Dragon” rating for speech accuracy by Nuance
- Pro-Flex wire microphone boom for perfect placement
- 40 mm stereo speakers with deep bass sound deliver crystal clear audio
- Comfortable foam ear cushions
- Reversible for left or right side usage
- Stainless steel adjustable headband folds flat for storage
- Convenient in-line volume and mute controls
- Extra long 8-foot shielded cable with color-coded 3.5 mm plugs for PC use

PARAMETER	VALUE
Connections	
Microphone Plug 3.5 mm	Pink (mic)
Speaker Plug 3.5 mm	Green (audio)
Microphone	
Noise Cancellation	5 dB/octave
Frequency Range	100-10,000 Hz
Electrical Signal-to-Noise Ratio	>60 dB
Sensitivity at 1kHz (0 dB=1V/Pa)	-44 dB
Current Consumption	<0.5 mA
Speakers	
Frequency Range	50-20,000 Hz
Coil Resistance	32 ohm
Sound Output from 1kHz 1mW Input (0 dB=20 µPa)	114 dB
Maximum Input Power	40 mW



PROPRIETARY
MICROPHONE DESIGN



COLOR-CODED PLUGS
FOR PC USE



IN-LINE VOLUME CONTROL



Education



Speech
Recognition



Video
Conferencing



Computer
Gaming



Music
Listening

Andrea Communications LLC
140 Finn Court • Farmingdale, New York 11735
800.442.7787 • sales@andreacommunications.com
www.andreacommunications.com

